

# MAKEN

## DT-100U/USB

# Cash Drawer Trigger

### Make It Happen

INNOVATION QUALITY SERVICE

### Introduction:

DT-100U Cash Drawer Trigger is designed to provide USB interfacing to the cash drawer. This allows the cash drawer, which is previously connected to POS printer or cash register, to be directly connected to a USB port of the computer. This means through the DT-100U the cash drawer can be directly connected to the computer when there is no printer used in the POS system.

The DT-100U USB Trigger Module uses a Virtual Serial Port Driver, making it appear to software like a standard RS232 Serial Port. This way existing POS Software can communicate with the USB Cash Drawer Trigger as though connected to a Serial Port. A unique serial number is assigned to each USB Trigger Module and the Driver Software will assign the next available Serial Port to each device it recognizes (multiple Triggers can be used on one PC).

### Features:

- Cash drawer can be directly connected to the computer with DT-100U
- Powered by the USB bus, external power is not required.
- Allows for "Hot Plugging", Plug and Play connectivity.
- No need to set the COM property.
- Suitable to any CASH DRAWER command. Write any data to drawer COM port will open the cash drawer.

### Specifications:

Dimension	Interface Module: 68 (h) × 44 (w) × 25 (h) mm
Weight	80 grams (including cable)
Color	Black
Computer interface	USB
Power Requirement	5V 200mA (max)
Cash Drawer	Connector: RJ12
	Rating: suits 12 Volts, 24 Volts
	Repeat rate: 5 seconds (Max)
Environment	Operating Temp: 0~55°C
	Storage Temp: -10~55°C
	Humidity: 10~90% relative

### Reference Pictures:



**Xiamen Maken Tech Co., Ltd.**

No.77, Huli Industrial Zone, Xike,

Tong'an District, Xiamen 361100

Fujian China

Tel: +86-592-5768733

Fax: +86-592-5768735

www.maken.com.cn

E-mail: export@maken.com.cn

*Specifications are subjected to change without notice.*

